

Electrical Characteristics:

Frequency	SRL	Return Loss	Attenuation	NEXT	PS-NEXT	ELFEXT	PS-ELFEXT	ACR	PS-ACR
	dB	dB	dB/100m	dB	dB	dB	dB	dB	dB
MHz	Minimum	Minimum	Maximum	Minimum	Minimum	Minimum	Minimum	Minimum	Minimum
1	23.0	20.0	2.0	70.3	68.3	63.8	60.8	68.3	66.3
4	23.0	20.3	4.0	61.3	59.3	51.7	48.7	57.3	55.3
10	23.0	25.0	6.4	55.3	53.3	43.8	40.8	48.9	46.9
16	23.0	25.0	8.2	52.3	50.3	39.7	36.7	44.1	42.1
20	23.0	25.0	9.2	50.8	48.8	37.7	34.7	41.6	39.6
31.25	21.1	23.6	11.7	47.9	45.9	33.9	30.9	36.2	34.2
62.5	18.1	21.5	16.9	43.4	41.4	27.8	24.8	26.5	24.5
100	16.0	20.1	21.9	40.3	38.3	23.8	20.8	18.4	16.4
250	12.0	17.3	36.8	34.3	32.3	15.8	12.8	---	---
300	11.2	16.8	40.9	33.2	31.2	14.2	11.2	---	---
350	10.6	16.3	44.8	32.2	30.2	12.9	9.9	---	---